

Metalogix® StoragePoint 5.9.1

## EMC Isilon Adapter Guide



© 2020 Quest Software Inc. ALL RIGHTS RESERVED.

This guide contains proprietary information protected by copyright. The software described in this guide is furnished under a software license or nondisclosure agreement. This software may be used or copied only in accordance with the terms of the applicable agreement. No part of this guide may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording for any purpose other than the purchaser's personal use without the written permission of Quest Software Inc.

The information in this document is provided in connection with Quest Software products. No license, express or implied, by estoppel or otherwise, to any intellectual property right is granted by this document or in connection with the sale of Quest Software products. EXCEPT AS SET FORTH IN THE TERMS AND CONDITIONS AS SPECIFIED IN THE LICENSE AGREEMENT FOR THIS PRODUCT, QUEST SOFTWARE ASSUMES NO LIABILITY WHATSOEVER AND DISCLAIMS ANY EXPRESS, IMPLIED OR STATUTORY WARRANTY RELATING TO ITS PRODUCTS INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTY OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, OR NON-INFRINGEMENT. IN NO EVENT SHALL QUEST SOFTWARE BE LIABLE FOR ANY DIRECT, INDIRECT, CONSEQUENTIAL, PUNITIVE, SPECIAL OR INCIDENTAL DAMAGES (INCLUDING, WITHOUT LIMITATION, DAMAGES FOR LOSS OF PROFITS, BUSINESS INTERRUPTION OR LOSS OF INFORMATION) ARISING OUT OF THE USE OR INABILITY TO USE THIS DOCUMENT, EVEN IF QUEST SOFTWARE HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES. Quest Software makes no representations or warranties with respect to the accuracy or completeness of the contents of this document and reserves the right to make changes to specifications and product descriptions at any time without notice. Quest Software does not make any commitment to update the information contained in this document.

If you have any questions regarding your potential use of this material, contact:

Quest Software Inc.  
Attn: LEGAL Dept.  
4 Polaris Way  
Aliso Viejo, CA 92656

Refer to our Web site (<https://www.quest.com>) for regional and international office information.

#### Patents

Quest Software is proud of our advanced technology. Patents and pending patents may apply to this product. For the most current information about applicable patents for this product, please visit our website at <https://www.quest.com/legal>.

#### Trademarks

Quest, the Quest logo, and Metalogix are trademarks and registered trademarks of Quest Software Inc. and its affiliates. For a complete list of Quest marks, visit <https://www.quest.com/legal/trademark-information.aspx>. All other trademarks and registered trademarks are property of their respective owners.

Metalogix® StoragePoint

Updated February 2020

Version 5.9

# Contents

<b>Isilon Adapter Configuration</b> .....	<b>4</b>
Isilon Adapter Connection String Parameters .....	6
Example Storage Endpoint Using Isilon .....	10
Retention Promotion from IMP .....	11
Appendix: Troubleshooting .....	12
Problem: Receiving errors on storage or retrieval of externalized content .....	12
<b>About Us</b> .....	<b>13</b>
Contacting Quest .....	13
Technical Support Resources .....	13

---


# Isilon Adapter Configuration

This section will provide you details on how to configure a storage endpoint's connection string to utilize the EMC Isilon Adapter. Please refer to the StoragePoint Reference Guide for information on managing Storage Endpoints.

On the Application Management page, click *Storage and Backup Endpoints*.

Click *Create New Endpoint* or click the name of an existing storage endpoint that you want to edit.

Click the *Show* link next to the Advanced Adapter Settings to see the additional fields.

Adapter  
EMCIsilon  

Adapter Settings  Show Connection String

Host

Share


Directory

Port

Use SSL  
No

User

Password

Retention  
 None  
 Date Format  
  
 Duration/Interval  Day(s)

**Advanced Adapter Settings** *(Hide)*

Buffer Size

# Isilon Adapter Connection String Parameters

Setting	Value/Options
<p>Name</p>	<p>Enter the unique name of the Storage or Backup Endpoint.</p>
<p>Type</p> <div data-bbox="204 584 544 685"> <p>Type</p> <p><input checked="" type="radio"/> Primary <input type="radio"/> Backup</p> </div> <p>See Backup Services Settings in the Reference Guide for more information on how Backup Endpoints are used.</p>	<p><i>Primary</i>– this endpoint will be available for externalization when creating storage profiles.</p> <p><i>Backup</i>– this endpoint will be in the Backup Services dropdown on the profile page.</p> <p>The selection is locked down when saving.</p>
<p>Status</p> <div data-bbox="204 1048 611 1167"> <p>Status</p> <p>Online</p> </div>	<p><i>Online</i>– Storage Endpoint should be available to associate to a Storage Profile and accept BLOBs. (default)</p> <p><i>Offline (Read Only)</i>– A storage endpoint can be configured, but not made available for externalizing content. The BLOBs already on the endpoint are still read only.</p>
<p>Adapter</p> <div data-bbox="204 1473 579 1570"> <p>EMCIsilon</p> </div>	<p>Select the adapter for the endpoint that is being created.</p>
<p>Host</p> <div data-bbox="204 1615 874 1711"> <p>enter IP address or host name for the cluster</p> </div>	<p>IP or DNS name chosen at the time the storage solution was provisioned which represents the Isilon access point.</p> <p>Single host examples:</p> <p>mycluster.company.com</p> <p>Or</p>

Setting	Value/Options
	192.168.1.42
<p>Share</p> <input data-bbox="236 434 845 474" type="text" value="enter Isilon share name"/>	Enter the Isilon share that will be used to hold content specific to this endpoint.
<p>Directory</p> <input data-bbox="236 604 855 645" type="text" value="enter Isilon share directory (optional)"/>	If needed, specify the path within the Share listed above.
<p>Port</p> <input data-bbox="236 761 552 801" type="text" value="enter the port number"/>	Enter the port number of the Isilon access point.
<p>Use SSL</p> <input data-bbox="245 936 335 967" type="button" value="No"/>	Select whether or not SSL is required to access the Isilon storage.
<p>User</p> <input data-bbox="236 1088 845 1128" type="text" value="enter the username to access Isilon"/> <p>Password</p> <input data-bbox="236 1182 845 1223" type="text" value="enter the password to access Isilon"/>	Enter the connection information for accessing the Isilon storage solution, including domain if necessary.
<p>Retention</p> <p><input checked="" data-bbox="252 1339 274 1370" type="radio"/> None</p> <p><input data-bbox="252 1384 274 1415" type="radio"/> Date Format</p> <input data-bbox="290 1424 577 1464" type="text"/> <p><input data-bbox="252 1473 274 1505" type="radio"/> Duration/Interval <input data-bbox="494 1464 603 1505" type="text"/> <input data-bbox="632 1473 778 1505" type="button" value="Day(s)"/></p>	<p>If supplied, the Isilon adapter will calculate and supply a retention policy, also known as SmartLock, when saving content. Possible settings are:</p> <p>None</p> <p>[DateFormat] example: <i>Retention=*08/31/2009;</i></p> <p>[Duration][Interval] example: <i>Retention=5D;</i></p> <p>[Interval] may be days (D), months (M) or years (Y).</p>

Setting	Value/Options
<p><b>Advanced Adapter Settings</b> <i>(Hide)</i></p> <p>Buffer Size</p> <input data-bbox="236 376 544 423" type="text" value="8192"/>	<p>Click Show to see the buffer size field. The buffer size field limits the amount of resources used to externalize data to the Isilon endpoint.</p>
<p>Is WORM Device</p> <input data-bbox="300 636 392 674" type="button" value="No"/>	<p>If the endpoint is on a WORM (Write Once, Read Many) device, Unused BLOB Cleanup will ignore this endpoint.</p>
<p>Folder Content in BLOB Store</p> <input data-bbox="236 815 323 853" type="button" value="Yes"/> <p>Folder Scheme</p> <input data-bbox="236 904 560 943" type="text" value="YYYY/MM/DD/HH/MM"/>	<p><i>No</i>– Externalized content BLOBs are not placed in folders.</p> <p><i>Yes</i>– Externalized content BLOBs are placed in folders (default).</p> <p>If <i>Folder Content in BLOB Store</i> is <i>Yes</i> then you can select a date/time folder scheme from the dropdown.</p> <p>YYYY/MM/DD/HH/MM is the default.</p>
<p><input data-bbox="245 1413 536 1451" type="button" value="Test Storage Settings"/></p>	<p>The Test Storage Settings button can be used at this point, or after completing the endpoint configuration, to verify that the endpoint is accessible.</p>
<p>Compress Content in BLOB Store</p> <input data-bbox="236 1733 323 1771" type="button" value="No"/> <p><i>Content is compressed using the GZip/Deflate method.</i></p>	<p><i>No</i>– Externalized content BLOBs are not compressed (default).</p> <p><i>Yes</i>– Externalized content BLOBs are compressed.</p>



Setting	Value/Options
<p>Encryption Method for Content in BLOB Store</p> <p>None</p>	<p><i>None</i>– Encryption will not be applied to externalized BLOBs (default).</p> <p><i>AES (128 bit)</i>– 128 bit AES encryption will be applied to externalized BLOBs.</p> <p><i>AES (256 bit)</i>– 256 bit AES encryption will be applied to externalized BLOBs.</p>
<p>Encryption Key Passphrase</p> <p>Generate Key</p> <p><i>Enter a passphrase to be used to generate a key or leave blank to generate a random key. The passphrase entered is <b>not</b> saved with the Endpoint.</i></p>	<p>Enter a passphrase to use when generating the encryption key. Using a passphrase will help you re-create the encryption key if necessary. You can generate a random key by leaving the box blank and clicking the <i>Generate Key</i> button. The encryption key passphrase will be hidden.</p>
<p>Generate warning notification if:</p> <p><input checked="" type="checkbox"/> 10 or more successive errors are encountered</p> <p><input checked="" type="checkbox"/> there is less than 10 <input checked="" type="radio"/> MB <input type="radio"/> % of free space</p>	<p>A warning email can be sent if it encounters errors.</p>
<p>Automatically take endpoint offline if:</p> <p><input checked="" type="checkbox"/> 25 or more successive errors are encountered</p> <p><input checked="" type="checkbox"/> there is less than 1 <input checked="" type="radio"/> MB <input type="radio"/> % of free space</p>	<p>An online storage endpoint can be automatically taken offline if it encounters errors. If a storage endpoint is taken offline automatically, BLOBs that were intended to be written to that endpoint will go to the content database.</p>

Setting	Value/Options
<p>Send Offline Notifications to:</p> <p><input checked="" type="checkbox"/> Use Notification Defaults</p> <p>Additional Contacts</p> <p><u>admin@company.com</u></p> <p><i>Provide a semi-colon delimited list of e-mail addresses.</i></p>	<p>Default email addresses for system error and offline notification can be entered. Check the box to include the list of Default Notification Contacts specified on the General Settings page.</p>

## Example Storage Endpoint Using Isilon

Adapter  
 ?

**Adapter Settings**  Show Connection String

Host

Share

Directory

Port

Use SSL

User

Password

Retention  
 None  
 Date Format  
   
 Duration/Interval

Click the *Show Connection String* checkbox to edit the connection string. Otherwise, fill in the connection fields shown for the adapter selected. Notice that the connection string parameters are

name/value pairs separated by semi-colons when editing using the Show Connection String option.

NOTE: Adapter parameters are not case-sensitive.

NOTE: You should always use a passphrase when generating encryption keys. The passphrase gives you a means of re-creating keys should they become unrecoverable or corrupt. It is very important to remember or record the passphrase outside of Metalogix StoragePoint. Otherwise, encrypted content could become irretrievable in the event of a database failure.

If you choose to externalize content you should test the storage profile settings by clicking the *Test Storage Settings* button. A message under the button will indicate whether or not the test was successful. If the test fails the message will include the error that was the root cause of the failure.

NOTE: When testing access to an endpoint from within Central Administration, the Identity of the Application Pool hosting the Central Administration Site is the one that is being used for the test. If there are different Identities used for other Web Applications in the Farm then those identities will also need access but cannot be tested from within Central Admin itself. See BLOB Store Security and Metalogix StoragePoint Required Privileges in the Metalogix StoragePoint Reference Guide.

## Retention Promotion from IMP

If retention settings have been configured in the SharePoint site or library, those retention settings will stay with the BLOB when it goes to the endpoint. To enable this, there is a box on the endpoint screen, when adding the endpoint to the profile. If the profile already exists, with the endpoint added, the feature can still be enabled, but will only be applied to BLOBs created after the feature is enabled.

1. Open or create the profile.
2. Add the endpoint to the profile.
3. On the endpoint screen, at the bottom, will be an option to Enable Retention Promotion from IMP. Check this box.

## Appendix: Troubleshooting

### Problem: Receiving errors on storage or retrieval of externalized content

Wherever possible, StoragePoint surfaces error messages returned by the adapter either directly to the user or within the SharePoint ULS logs. You should refer to your storage platform/provider documentation for resolution to errors logged by the adapter.

---

## About Us

### We are more than just a name

We are on a quest to make your information technology work harder for you. That is why we build community-driven software solutions that help you spend less time on IT administration and more time on business innovation. We help you modernize your data center, get you to the cloud quicker and provide the expertise, security and accessibility you need to grow your data-driven business. Combined with Quest's invitation to the global community to be a part of its innovation, and our firm commitment to ensuring customer satisfaction, we continue to deliver solutions that have a real impact on our customers today and leave a legacy we are proud of. We are challenging the status quo by transforming into a new software company. And as your partner, we work tirelessly to make sure your information technology is designed for you and by you. This is our mission, and we are in this together. Welcome to a new Quest. You are invited to Join the Innovation™.

### Our brand, our vision. Together.

Our logo reflects our story: innovation, community and support. An important part of this story begins with the letter Q. It is a perfect circle, representing our commitment to technological precision and strength. The space in the Q itself symbolizes our need to add the missing piece — you — to the community, to the new Quest.

### Contacting Quest

For sales or other inquiries, visit [www.quest.com/contact](http://www.quest.com/contact).

### Technical Support Resources

Technical support is available to Quest customers with a valid maintenance contract and customers who have trial versions. You can access the Quest Support Portal at <https://support.quest.com>

The Support Portal provides self-help tools you can use to solve problems quickly and independently, 24 hours a day, 365 days a year. The Support Portal enables you to:

- Submit and manage a Service Request
- View Knowledge Base articles

- Sign up for product notifications
- Download software and technical documentation
- View how-to-videos
- Engage in community discussions
- Chat with support engineers online
- View services to assist you with your product