

Metalogix® StoragePoint 5.9.

EMCECS Adapter Guide



© 2021 Quest Software Inc. ALL RIGHTS RESERVED.

This guide contains proprietary information protected by copyright. The software described in this guide is furnished under a software license or nondisclosure agreement. This software may be used or copied only in accordance with the terms of the applicable agreement. No part of this guide may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording for any purpose other than the purchaser's personal use without the written permission of Quest Software Inc.

The information in this document is provided in connection with Quest Software products. No license, express or implied, by estoppel or otherwise, to any intellectual property right is granted by this document or in connection with the sale of Quest Software products. EXCEPT AS SET FORTH IN THE TERMS AND CONDITIONS AS SPECIFIED IN THE LICENSE AGREEMENT FOR THIS PRODUCT, QUEST SOFTWARE ASSUMES NO LIABILITY WHATSOEVER AND DISCLAIMS ANY EXPRESS, IMPLIED OR STATUTORY WARRANTY RELATING TO ITS PRODUCTS INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTY OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, OR NON-INFRINGEMENT. IN NO EVENT SHALL QUEST SOFTWARE BE LIABLE FOR ANY DIRECT, INDIRECT, CONSEQUENTIAL, PUNITIVE, SPECIAL OR INCIDENTAL DAMAGES (INCLUDING, WITHOUT LIMITATION, DAMAGES FOR LOSS OF PROFITS, BUSINESS INTERRUPTION OR LOSS OF INFORMATION) ARISING OUT OF THE USE OR INABILITY TO USE THIS DOCUMENT, EVEN IF QUEST SOFTWARE HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES. Quest Software makes no representations or warranties with respect to the accuracy or completeness of the contents of this document and reserves the right to make changes to specifications and product descriptions at any time without notice. Quest Software does not make any commitment to update the information contained in this document.

If you have any questions regarding your potential use of this material, contact:

Quest Software Inc.
Attn: LEGAL Dept.
4 Polaris Way
Aliso Viejo, CA 92656

Refer to our Web site (<https://www.quest.com>) for regional and international office information.

Patents

Quest Software is proud of our advanced technology. Patents and pending patents may apply to this product. For the most current information about applicable patents for this product, please visit our website at <https://www.quest.com/legal>.

Trademarks

Quest, the Quest logo, and Metalogix are trademarks and registered trademarks of Quest Software Inc. and its affiliates. For a complete list of Quest marks, visit <https://www.quest.com/legal/trademark-information.aspx>. All other trademarks and registered trademarks are property of their respective owners.

Legend

 **CAUTION:** A caution icon indicates potential damage to hardware or loss of data if instructions are not followed.

 **IMPORTANT, NOTE, TIP, MOBILE OR VIDEO:** An information icon indicates supporting information.

Contents

EMCECS Adapter Configuration	4
EMCECS Adapter Connection String Parameters	6
Example Storage Endpoint using EMCECS Adapter	10
Appendix: Troubleshooting	13
Problem: Receiving errors on storage or retrieval of externalized content.	13
About Us	14
Contacting Quest	14
Technical Support Resources	14

EMCECS Adapter Configuration

This section will provide you details on how to configure a storage endpoint's connection string to utilize the EMCECS Adapter, which is standard with StoragePoint. Please refer to the StoragePoint Reference Guide for information on managing Storage Endpoints.

For more information on the EMCECS implementation, see the EMC [documentation](#).

On the Application Management page, click *Storage and Backup Endpoints*.

Click *Create New Endpoint* or click the name of an existing storage endpoint that you want to edit.

Click the *Show* link next to the Advanced Adapter Settings to see the additional fields.

Storage Settings

Please provide storage device settings in this section.

Adapter
EMCECS

Adapter Settings Show Connection String
EMCECSS3

Access Key
enter an account Access Key

Secret Key
enter an account Secret Key

Bucket Name
enter an account Bucket name
(Lowercase letters and "DNS Friendly" naming highly recommended.)

Advanced Adapter Settings *(Hide)*

Use SSL
True

Proxy URI
enter simple proxy for communication (optional)

S3 Host
specifies explicitly the Host to use (optional)

S3 Port Number
enter port number (optional)

Strict SSL
No

Region
Enter Region Name.

Storage Settings

Please provide storage device settings in this section.

Adapter
EMCECS

Adapter Settings Show Connection String
EMCECSAtmos

UID
enter an account UID

Key
enter an account Key

Advanced Adapter Settings *(Hide)*

Base URI
accesspoint.emccis.com



Root
enter an account Root value (optional)

Use SSL
No

Port
80

Verify Hash
No

EMCECS Adapter Connection String Parameters

Setting	Value/Options
Name	Enter the unique name of the Storage or Backup Endpoint.
Type  See Backup Services Settings in the Reference Guide for more information on how Backup Endpoints are used.	<p><i>Primary</i>– this endpoint will be available for externalization when creating storage profiles.</p> <p><i>Backup</i>– this endpoint will be in the Backup Services dropdown on the profile page.</p> <p>The selection is locked down when saving.</p>
Status 	<p><i>Online</i>– Storage Endpoint should be available to associate to a Storage Profile and accept BLOBs. (default)</p> <p><i>Offline (Read Only)</i>– A storage endpoint can be configured, but not made available for externalizing content. The BLOBs already on the endpoint are still read only.</p>
Adapter 	Select the adapter for the endpoint that is being created.
Adapter Settings 	After selecting the Adapter EMCECS, an additional dropdown selection must be made to designate if Atmos or S3 protocol will be used for the endpoint configuration.
UID 	ATMOS: The username to use when connecting to the server. This is equivalent to the Token ID provided with your Atmos online account.

Setting	Value/Options
<p>Key</p> <input data-bbox="236 338 855 376" type="text"/>	<p>ATMOS: The base64 encoded shared secret to use when signing requests to the server.</p>
<p>Advanced Adapter Settings <i>(Hide)</i></p> <p>Base URI</p> <input data-bbox="236 539 847 577" type="text" value="accesspoint.emccis.com"/>	<p>ATMOS: IP address or host name that represents the Atmos instance or specific node to be used. Default = accesspoint.emccis.com.</p>
<p>Root</p> <input data-bbox="236 703 847 741" type="text"/>	<p>ATMOS: The starting folder/container within your Atmos namespace under which all folders and files will be created.</p>
<p>Use SSL</p> <input data-bbox="236 913 325 952" type="button" value="No"/>	<p>ATMOS: <i>(yes/no)</i> Determines whether or not the adapter negotiates an SSL connection for all data (and metadata) transfers. Default = No.</p>
<p>Port</p> <input data-bbox="261 1128 751 1182" type="text" value="enter a port number (optional)"/>	<p>ATMOS: The port on the server to communicate with. Default = 9022 (9023 if UseSSL is Yes).</p>
<p>Verify Hash</p> <input data-bbox="236 1310 325 1348" type="button" value="No"/>	<p>ATMOS: <i>(yes/no)</i> Includes a checksum operation after each blob transfer. Allows the adapter to detect and log data integrity errors immediately. Default = No.</p>
<p>Adapter Settings</p> <div data-bbox="225 1518 437 1581" style="border: 1px solid black; padding: 2px;"> EMCECSAtmos EMCECSS3 </div>	<p>S3 Options</p> <p>i NOTE: The EMCECS adapter can be used with the Dell ECS device, using the EMCECSS3 Adapter Settings.</p>
<p>Access Key</p> <input data-bbox="236 1861 847 1899" type="text"/>	<p>S3: The Access Key ID provided when you signed up for the S3 service. Required.</p>

Setting	Value/Options
<p>Secret Key</p> <input data-bbox="236 342 858 383" type="text"/>	<p>S3: The Secret Access Key provided when you signed up for the S3 service. Required.</p>
<p>Bucket Name</p> <input data-bbox="236 506 847 539" type="text" value="8192"/> <p><i>(Lowercase letters and "DNS Friendly" naming highly recommended.)</i></p>	<p>S3: The container within your S3 account where content associated with a storage profile will be stored. Bucket names are case sensitive and unique across the entire S3 service namespace.</p>
<p>Advanced Adapter Settings <i>(Hide)</i></p> <p>Use SSL</p> <input data-bbox="236 815 344 853" type="text" value="True"/>	<p>S3: (<i>true/false</i>) Determines whether or not the adapter negotiates an SSL connection for all data (and metadata) transfers. Default = False.</p>
<p>Proxy URI</p> <input data-bbox="248 999 863 1039" type="text"/>	<p>S3: Used to take the URL (optionally including a port) of a simple non-authenticating proxy that will be used when communicating with EMCECS services.</p>
<p>S3 Host</p> <input data-bbox="248 1245 863 1285" type="text"/>	<p>IP or DNS name that represents the access point for the Amazon AWS service.</p>
<p>S3 Port Number</p> <input data-bbox="236 1413 363 1453" type="text"/>	<p>Port used to access the S3 service. Default = 9020 for http and 9021 for https.</p>
<p>Strict SSL</p> <input data-bbox="261 1615 352 1655" type="text" value="No"/>	<p><i>(Yes/No)</i> If <i>UseSSL</i> is <i>Yes</i>, the <i>StrictSSL</i> flag controls whether or not the use of "self-issued" or otherwise suspicious certificates on the system will be tolerated.</p>
<p>Region</p> <input data-bbox="236 1843 858 1883" type="text" value="Enter Region Name."/>	<p>Used in AWS4 request signing, this is an optional property; change it only if the region cannot be determined from the service endpoint.</p>

Setting	Value/Options
	For custom or private clouds or where StoragePoint cannot automatically retrieve the region because of security or permission reasons.

Example Storage Endpoint using EMCECS Adapter

Adapter

EMCECS 

Adapter Settings Show Connection String

EMCECSS3 

Access Key

username

Secret Key

.....

Bucket Name

bucketname

(Lowercase letters and "DNS Friendly" naming highly recommended.)

Advanced Adapter Settings *(Hide)*

Use SSL

True

Proxy URI

enter simple proxy for communication (optional)

S3 Host

http://172.1.2.3

S3 Port Number

1230

Strict SSL

No

Region

Enter Region Name.

Adapter

EMCECS 

Adapter Settings Show Connection String

EMCECSAtmos 

UID

ask4da6lksdjh2iu78rhr56ga89/usersatmos

Key

.....

Advanced Adapter Settings *(Hide)*

Base URI

accesspoint.emcecs.com

Root

enter an account Root value (optional)

Use SSL

No

Port

1040

Verify Hash

No

Click the *Show Connection String* checkbox to edit the connection string. Otherwise, fill in the connection fields shown for the adapter selected. Notice that the connection string parameters are name/value pairs separated by semi-colons.

Status
Online S3

Adapter
EMCECS 

Adapter Settings Show Connection String

Connection

```
ACCESSKEY=username;SECRETKEY=*****;BUCKET=b  
ucketname;USESSL=True;PROXY=;HOST=http://172.  
1.2.3;PORT=1230;PROTOCOL=EMCECSS3;;STRICTSS  
L=False;REGION=
```

Provide adapter-specific connection attributes. Please refer to the adapter documentation for connection string details.

Adapter
EMCECS  Atmos

Adapter Settings Show Connection String

Connection

```
UID=ask4da6lksdjh2iu78rhr56ga89/usersatmos;KEY  
=*****;BASEURI=accesspoint.emcecs.com;PORT=10  
40;ROOT=;USESSL=False;VERIFYHASH=False;PROT  
OCOL=EMCECSAtmos;
```

Provide adapter-specific connection attributes. Please refer to the adapter documentation for connection string details.

i | **NOTE:** Adapter parameters are not case-sensitive.

i | **NOTE:** You should always use a passphrase when generating encryption keys. The passphrase gives you a means of re-creating keys should they become unrecoverable or corrupt. It is very important to remember or record the passphrase outside of Metalogix StoragePoint. Otherwise, encrypted content could become irretrievable in the event of a database failure.

If you choose to externalize content you should test the storage profile settings by clicking the *Test Storage Settings* button. A message under the button will indicate whether or not the test was successful. If the test fails the message will include the error that was the root cause of the failure.

i **NOTE:** When testing access to an endpoint from within Central Administration, the Identity of the Application Pool hosting the Central Administration Site is the one that is being used for the test. If there are different Identities used for other Web Applications in the Farm then those identities will also need access but cannot be tested from within Central Admin itself. See BLOB Store Security and Metalogix StoragePoint Required Privileges in the Metalogix StoragePoint Reference Guide.

Appendix: Troubleshooting

Problem: Receiving errors on storage or retrieval of externalized content.

Wherever possible, StoragePoint surfaces error messages returned by the adapter either directly to the user or within the SharePoint ULS logs. You should refer to your storage platform/provider documentation for resolution to errors logged by the adapter.

About Us

Quest creates software solutions that make the benefits of new technology real in an increasingly complex IT landscape. From database and systems management, to Active Directory and Office 365 management, and cyber security resilience, Quest helps customers solve their next IT challenge now. Around the globe, more than 130,000 companies and 95% of the Fortune 500 count on Quest to deliver proactive management and monitoring for the next enterprise initiative, find the next solution for complex Microsoft challenges and stay ahead of the next threat. Quest Software. Where next meets now. For more information, visit www.quest.com.

Contacting Quest

For sales or other inquiries, visit www.quest.com/contact.

Technical Support Resources

Technical support is available to Quest customers with a valid maintenance contract and customers who have trial versions. You can access the Quest Support Portal at <https://support.quest.com>

The Support Portal provides self-help tools you can use to solve problems quickly and independently, 24 hours a day, 365 days a year. The Support Portal enables you to:

- Submit and manage a Service Request
- View Knowledge Base articles
- Sign up for product notifications
- Download software and technical documentation
- View how-to-videos
- Engage in community discussions
- Chat with support engineers online
- View services to assist you with your product