

Metalogix® StoragePoint 5.9

Hitachi HCP or HCAP Adapter Guide



© 2019 Quest Software Inc. ALL RIGHTS RESERVED.

This guide contains proprietary information protected by copyright. The software described in this guide is furnished under a software license or nondisclosure agreement. This software may be used or copied only in accordance with the terms of the applicable agreement. No part of this guide may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording for any purpose other than the purchaser's personal use without the written permission of Quest Software Inc.

The information in this document is provided in connection with Quest Software products. No license, express or implied, by estoppel or otherwise, to any intellectual property right is granted by this document or in connection with the sale of Quest Software products. EXCEPT AS SET FORTH IN THE TERMS AND CONDITIONS AS SPECIFIED IN THE LICENSE AGREEMENT FOR THIS PRODUCT, QUEST SOFTWARE ASSUMES NO LIABILITY WHATSOEVER AND DISCLAIMS ANY EXPRESS, IMPLIED OR STATUTORY WARRANTY RELATING TO ITS PRODUCTS INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTY OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, OR NON-INFRINGEMENT. IN NO EVENT SHALL QUEST SOFTWARE BE LIABLE FOR ANY DIRECT, INDIRECT, CONSEQUENTIAL, PUNITIVE, SPECIAL OR INCIDENTAL DAMAGES (INCLUDING, WITHOUT LIMITATION, DAMAGES FOR LOSS OF PROFITS, BUSINESS INTERRUPTION OR LOSS OF INFORMATION) ARISING OUT OF THE USE OR INABILITY TO USE THIS DOCUMENT, EVEN IF QUEST SOFTWARE HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES. Quest Software makes no representations or warranties with respect to the accuracy or completeness of the contents of this document and reserves the right to make changes to specifications and product descriptions at any time without notice. Quest Software does not make any commitment to update the information contained in this document.

If you have any questions regarding your potential use of this material, contact:

Quest Software Inc.
Attn: LEGAL Dept.
4 Polaris Way
Aliso Viejo, CA 92656

Refer to our Web site (<https://www.quest.com>) for regional and international office information.

Patents

Quest Software is proud of our advanced technology. Patents and pending patents may apply to this product. For the most current information about applicable patents for this product, please visit our website at <https://www.quest.com/legal>.

Trademarks

Quest, the Quest logo, and Metalogix are trademarks and registered trademarks of Quest Software Inc. and its affiliates. For a complete list of Quest marks, visit <https://www.quest.com/legal/trademark-information.aspx>. All other trademarks and registered trademarks are property of their respective owners.

Metalogix® StoragePoint

Updated August 2019

Version 5.9

Contents

| | |
|---|-----------|
| HCAP Adapter Configuration | 4 |
| HCP/HCAP Adapter Connection String Parameters | 6 |
| Example Storage Endpoint using HCP or HCAP Adapter | 13 |
| VerifyWrites | 14 |
| Retention Promotion from IMP | 15 |
| Event Based Retention | 15 |
| Appendix: Troubleshooting | 16 |
| Problem: Receive an error message when testing a storage profile. | 16 |
| Problem: Receiving errors on storage or retrieval of externalized content. | 16 |
| Problem: Newly uploaded content is not being archived as expected. | 16 |
| About Us | 18 |
| Contacting Quest | 18 |
| Technical Support Resources | 18 |

HCAP Adapter Configuration

This section will provide you details on how to configure a storage endpoint's connection string to utilize the Hitachi Adapter. Please refer to the StoragePoint Reference Guide for information on managing Storage Endpoints.

StoragePoint supports HCAP 5.x, HCP 6.x, HCP 7.x and HCP 8.x versions of the platform.

On the Application Management page, click *Storage and Backup Endpoints*.

Click *Create New Endpoint* or click the name of an existing storage endpoint that you want to edit.

Select HCP or HCAP for legacy adapters. Click the *Show* link next to the Advanced Adapter Settings to see the additional fields.

Adapter Settings Show Connection String

Hitachi Platform

HCP
 HCAP (legacy)

Host

Use SSL

User

Password

Advanced Adapter Settings [\(hide\)](#)

Root


Strict SSL

Timeout (in seconds)

Verify Hash

Retry

Retention

Delete Allowed
 Permanent
 Indefinite
 Date Format:

 Duration/Interval:

HCP-Specific

Hold Index Shred

Adapter Settings Show Connection String

Hitachi Platform

HCP

HCAP (legacy)

Host

Use SSL

Advanced Adapter Settings (Hide)

Root

Strict SSL

Timeout (in seconds)

UID

Verify Hash

Retry


Retention

Delete Allowed

Permanent

Indefinite






Date Format:




Duration/Interval:


HCP/HCAP Adapter Connection String Parameters





| Setting | Value/Options |
|---------|--|
| Name | Enter the unique name of the Storage or Backup Endpoint. |


| Setting | Value/Options |
|---|--|
| <p>Type</p>  <p>See Backup Services Settings in the Reference Guide for more information on how Backup Endpoints are used.</p> | <p><i>Primary</i>– this endpoint will be available for externalization when creating storage profiles.</p> <p><i>Backup</i>– this endpoint will be in the Backup Services dropdown on the profile page.</p> <p>The selection is locked down when saving.</p> |
| <p>Status</p>  | <p><i>Online</i>– Storage Endpoint should be available to associate to a Storage Profile and accept BLOBs. (default)</p> <p><i>Offline (Read Only)</i>– A storage endpoint can be configured, but not made available for externalizing content. The BLOBs already on the endpoint are still read only.</p> |
|  | <p>Select the adapter for the endpoint that is being created.</p> |
| <p>Host</p>  | <p>Fully qualified domain name that represents the HCP tenant namespace, or if HCAP (legacy) system is used, fully qualified domain name or IP address that represents legacy HCAP system.</p> |
| <p>Use SSL</p>  | <p><i>(yes/no)</i> – Determines whether or not the adapter negotiates an SSL connection for all data (and metadata) transfers. Default = No.</p> |

| Setting | Value/Options |
|---|---|
| <div data-bbox="209 297 564 398"> <p>User</p> <input type="text"/> </div> <div data-bbox="209 459 608 562"> <p>Password</p> <input type="password"/> </div> | <p>User login and password used to access the HCP system. Not applicable for HCAP (legacy) system.</p> <p>This needs to be a local tenent to the HCP system and cannot be a domain account.</p> |
| <div data-bbox="209 663 663 792"> <p>Advanced Adapter Settings <i>(Hide)</i></p> <p>Root</p> <input type="text"/> </div> | <p>Folder path to use when storing the SharePoint content under this profile. Facilitates the current best practice of dividing up the HCP/HCAP name-space by application. Please remember that HCP/HCAP paths and folder names are case sensitive.</p> |
| <div data-bbox="209 1086 387 1189"> <p>Strict SSL</p> <input type="button" value="No"/> </div> | <p><i>(Yes/No)</i> If <i>UseSSL</i> is <i>Yes</i>, the <i>StrictSSL</i> flag controls whether or not the use of "self-issued" or otherwise suspicious certificates on the HCP/HCAP system will be tolerated. Note that the default certificate out of the box with HCP/HCAP is self-issued and will not work unless this flag is set to No (default).</p> |
| <div data-bbox="209 1597 560 1700"> <p>Timeout (in seconds)</p> <input type="text" value="120"/> </div> | <p>Number of seconds to wait for a response to any request before considering it an excessively long wait and raising an error condition. Default = 120.</p> |

| Setting | Value/Options |
|---|--|
| <p>UID</p> <input data-bbox="236 344 518 383" type="text"/> | <p>Identifies the "owner" of all content uploaded with this adapter. See HCAP documentation for details on UID, GID and permissions semantics. By default permission checking is disabled on HCAP (legacy) systems. Not applicable to HCP.</p> |
| <p>Verify Hash</p> <input data-bbox="245 810 336 848" type="text" value="No"/> | <p>(<i>Yes/No</i>) If set to <i>Yes</i>, adds content integrity checking by comparing a locally computed hash for the file bits against the hash returned from HCP/HCAP during upload operations. Default = No.</p> |
| <p>Retry</p> <input data-bbox="245 1151 523 1189" type="text" value="3"/> | <p>Specifies the number of attempts to retry the network connection to HCP/HCAP before returning a failure result in case of network disruption or connectivity issues. Default = 3.</p> |
| <p>Retention</p> <p><input checked="" data-bbox="253 1507 277 1541" type="radio"/> Delete Allowed</p> <p><input data-bbox="253 1552 277 1585" type="radio"/> Permanent</p> <p><input data-bbox="253 1597 277 1630" type="radio"/> Indefinite</p> <p><input data-bbox="253 1641 277 1675" type="radio"/> Date Format:</p> <p><input data-bbox="292 1686 571 1724" type="text"/> </p> <p><input data-bbox="253 1736 277 1769" type="radio"/> Duration/Interval: <input data-bbox="507 1736 619 1769" type="text"/> <input data-bbox="627 1736 778 1769" type="text" value="Day(s)"/></p> | <p>If supplied, the HCP/HCAP adapter will calculate and supply a retention policy when saving content.</p> <p>Possible settings:</p> <p>Delete Allowed</p> <p>No special permissions are required to delete content on this endpoint.</p> <p>Permanent</p> |

| Setting | Value/Options |
|--|---|
| | <p>This maps to -1 or "Infinite retention, cannot be deleted" in HCP/HCAP.</p> <p>Indefinite</p> <p>This maps to -2 or "Initial Unspecified" in HCP/HCAP. Content cannot be deleted, but retention can be changed at a later time.</p> <p>Date Format</p> <p>This sets a date for the retention policy. Click the calendar icon to select a date, or type it like this example:</p> <p>08/31/2009</p> <p>Duration/Interval</p> <p>Type a number in the first box, and select an interval from the dropdown. The interval may be days (D), months (M) or years (Y).</p> <p>Example: 5D would equal 5 Days</p> <p>NOTE: You can NEVER shorten the retention period once it has been established, unless it was initially set to Indefinite.</p> |
|  <p>HCP-Specific <input type="checkbox"/> Hold  <input type="checkbox"/> Index <input type="checkbox"/> Shred</p> | <p>If Hold is set to true (checked) you can place an object on hold. An object that is on hold cannot be deleted, even by a privileged delete operation. Holding objects is particularly</p> |

| Setting | Value/Options |
|---|---|
| | useful when the objects are needed for legal discovery. |
|  | <p>If Index is set to true (checked), the metadata query engine indexes custom metadata. Having index set to true will speed-up metadata search experience.</p> |
|  | <p>If Shred is set to true (checked) all objects will be shredded when deleted.</p> <p>Shredding, also called secure deletion, is the process of deleting an object and overwriting the places where its copies were stored in such a way that none of its data or metadata, including custom metadata, can be reconstructed.</p> |
|  | <p>If the endpoint is on a WORM (Write Once, Read Many) device, Unused BLOB Cleanup will ignore this endpoint.</p> |
|  | <p><i>No</i>– Externalized content BLOBs are not placed in folders.</p> <p><i>Yes</i>– Externalized content BLOBs are placed in folders (default).</p> <p>If <i>Folder Content in BLOB Store</i> is <i>Yes</i> then you can select a date/time folder scheme from the dropdown.</p> |

| Setting | Value/Options |
|---|---|
| | YYYY/MM/DD/HH/MM is the default. |
|  | The Test Storage Settings button can be used at this point, or after completing the endpoint configuration, to verify that the endpoint is accessible. |
| <p>Compress Content in BLOB Store</p> <p><input type="button" value="No"/></p> <p><i>Content is compressed using the GZip/Deflate method.</i></p> | <p><i>No</i>– Externalized content BLOBs are not compressed (default).</p> <p><i>Yes</i>– Externalized content BLOBs are compressed.</p> |
| <p>Encryption Method for Content in BLOB Store</p> <p><input type="button" value="None"/></p> | <p><i>None</i>– Encryption will not be applied to externalized BLOBs (default).</p> <p><i>AES (128 bit)</i>– 128 bit AES encryption will be applied to externalized BLOBs.</p> <p><i>AES (256 bit)</i>– 256 bit AES encryption will be applied to externalized BLOBs.</p> |
| <p>Encryption Key Passphrase</p> <p><input type="text"/> <input type="button" value="Generate Key"/></p> <p><i>Enter a passphrase to be used to generate a key or leave blank to generate a random key. The passphrase entered is not saved with the Endpoint.</i></p> | Enter a passphrase to use when generating the encryption key. Using a passphrase will help you re-create the encryption key if necessary. You can generate a random key by leaving the box blank and clicking the <i>Generate Key</i> button. The encryption key passphrase will be hidden. |

| Setting | Value/Options |
|--|---|
| <p>Generate warning notification if:</p> <p><input checked="" type="checkbox"/> <input type="text" value="10"/> or more successive errors are encountered</p> <p><input checked="" type="checkbox"/> there is less than <input type="text" value="10"/> <input checked="" type="radio"/> MB <input type="radio"/> % of free space</p> | A warning email can be sent if it encounters errors. |
| <p>Automatically take endpoint offline if:</p> <p><input checked="" type="checkbox"/> <input type="text" value="25"/> or more successive errors are encountered</p> <p><input checked="" type="checkbox"/> there is less than <input type="text" value="1"/> <input checked="" type="radio"/> MB <input type="radio"/> % of free space</p> | An online storage endpoint can be automatically taken offline if it encounters errors. If a storage endpoint is taken offline automatically, BLOBs that were intended to be written to that endpoint will go to the content database. |
| <p>Send Offline Notifications to:</p> <p><input checked="" type="checkbox"/> Use Notification Defaults</p> <p>Additional Contacts</p> <p><input type="text" value="admin@company.com"/></p> <p><i>Provide a semi-colon delimited list of e-mail addresses.</i></p> | Default email addresses for system error and offline notification can be entered. Check the box to include the list of Default Notification Contacts specified on the General Settings page. |

Example Storage Endpoint using HCP or HCAP Adapter

Storage Settings
Provide general storage settings in this section

Adapter:


Adapter Settings Show Connection String

Host:

Advanced Adapter Settings [\(Show\)](#)

Click the *Show Connection String* checkbox to edit the connection string. Otherwise, fill in the connection fields shown for the adapter selected. Notice that the connection string parameters are

name/value pairs separated by semi-colons.



Storage Settings
Provide general storage settings in this section

Adapter
HcapRest

Adapter Settings Show Connection String

Connection
HOST=191.168.1.51;ROOT=;USESSL=False;STRICTSSL=False;TIMEOUT=120;UID=;VERIFYHASH=False;RETRY=3;RETENTION=;

Provide adapter-specific connection attributes. Please refer to the adapter documentation for connection string details.

NOTE: Adapter parameters are not case-sensitive.

NOTE: Clicking the Test Storage Settings button on a storage profile using the HCP Adapter could result in an error. The profile test performs several operations, including a delete operation. If you are setting a retention parameter on the connection string then you will receive an error letting you know that the delete failed. This should not be considered a failure of the test.

NOTE: You should always use a passphrase when generating encryption keys. The passphrase gives you a means of re-creating keys should they become unrecoverable or corrupt. It is very important to remember or record the passphrase outside of Metalogix StoragePoint. Otherwise, encrypted content could become irretrievable in the event of a database failure.

If you choose to externalize content you should test the storage profile settings by clicking the *Test Storage Settings* button. A message under the button will indicate whether or not the test was successful. If the test fails the message will include the error that was the root cause of the failure.

NOTE: When testing access to an endpoint from within Central Administration, the Identity of the Application Pool hosting the Central Administration Site is the one that is being used for the test. If there are different Identities used for other Web Applications in the Farm then those identities will also need access but cannot be tested from within Central Admin itself. See BLOB Store Security and Metalogix StoragePoint Required Privileges in the Metalogix StoragePoint Reference Guide.

VerifyWrites


This option posts back to StoragePoint to validate that the BLOB was written to the endpoint. It is not part of the connection string by default, but can be added by editing the connection string only; there is no user interface for this option. If verbose logging is enabled, the logs may contain information such as 'Written file verified as present: <filename>.'

VERIFYWRITES=true;

Retention Promotion from IMP

If retention settings have been configured in the SharePoint site or library, those retention settings will stay with the BLOB when it goes to the endpoint. To enable this, there is a box on the endpoint screen, when adding the endpoint to the profile. If the profile already exists, with the endpoint added, the feature can still be enabled, but will only be applied to BLOBs created after the feature is enabled.

1. Open or create the profile.
2. Add the endpoint to the profile.
3. On the endpoint screen, at the bottom, will be an option to Enable Retention Promotion from IMP. Check this box.




The screenshot shows a configuration window titled "Retention Promotion from IMP". On the left, there is explanatory text: "This Endpoint is capable promoting retention value from IMP. If you select this option retention will be set according to IMP. This value is applied only when BLOB is created." On the right, there is a checkbox labeled "Enable Retention Promotion from IMP".

Event Based Retention

EBR is a feature that can be configured for certain storage endpoints. In addition to the default retention that can be configured on the endpoint, certain actions like updating a field can update the content to specify a different retention period. The steps for configuring the adapter to support EBR are outlined below.

The endpoint must be added to the profile for the following steps to work.

1. Expand the Archiving section of the profile.
2. Set the Enable Archiving dropdown to Yes.
3. Click New Rule.
4. Click Change to select the scope of the rule, which can be as wide as the profile scope or as narrow as a list. Click Ok.
5. Select Metadata Change Rule and click New Condition.
6. By selecting the same endpoint that was added to the profile, a new field displays for designating EBR. Check the EBR box, select a field to base the retention on, and enter the number of days to which to update the retention time.



The screenshot shows a configuration window titled "Event Based Retention". On the left, there is text: "Specify event-based retention parameters to apply to the content if this condition is met." On the right, there is a checked checkbox labeled "Enable Event Based Retention for This Rule". Below the checkbox, there is a dropdown menu labeled "Select a Date Property to Base Retention On" with the selected option being "(From date of metadata change)". Below the dropdown, there is a plus sign, a text input field, and the word "Days".

7. Click OK on the Condition window.

8. Click OK on the Rule window.
9. Click Save on the archiving page.
10. (OPTIONAL) Select Immediately or schedule a timer job to run, to process existing content for this archiving rule. Click OK on the Process Existing page.

NOTE: Content retention is modified when the field changes, not when it is uploaded. Uploaded content will receive the default retention setting, but modifying the designated EBR field will update the retention setting for that content.

Appendix: Troubleshooting

Problem: Receive an error message when testing a storage profile.

When clicking the *Test Storage Settings* button on a storage profile using the HCP or HCAP adapter you receive an error similar to this:



This error is because a RETENTION value was specified on the storage profile's Connection String and StoragePoint cannot delete the externalized test file. This should be considered a successful test.

Problem: Receiving errors on storage or retrieval of externalized content.

Wherever possible, StoragePoint surfaces error messages returned by HCP/HCAP either directly to the user or within the SharePoint ULS logs. You should refer to your HCP/HCAP documentation for errors logged by the HCP/HCAP Adapter.

Problem: Newly uploaded content is not being archived as expected.

For event based retention to work, the item has to exist before it can be tagged with retention during the archive process. So if content is uploaded with a change to the metadata that would normally archive the item, it won't be archived. However, any subsequent change to the item will

flag it for archiving, and the next successful run of the content queue migrator will archive that content.

About Us

We are more than just a name

We are on a quest to make your information technology work harder for you. That is why we build community-driven software solutions that help you spend less time on IT administration and more time on business innovation. We help you modernize your data center, get you to the cloud quicker and provide the expertise, security and accessibility you need to grow your data-driven business. Combined with Quest's invitation to the global community to be a part of its innovation, and our firm commitment to ensuring customer satisfaction, we continue to deliver solutions that have a real impact on our customers today and leave a legacy we are proud of. We are challenging the status quo by transforming into a new software company. And as your partner, we work tirelessly to make sure your information technology is designed for you and by you. This is our mission, and we are in this together. Welcome to a new Quest. You are invited to Join the Innovation™.

Our brand, our vision. Together.

Our logo reflects our story: innovation, community and support. An important part of this story begins with the letter Q. It is a perfect circle, representing our commitment to technological precision and strength. The space in the Q itself symbolizes our need to add the missing piece — you — to the community, to the new Quest.

Contacting Quest

For sales or other inquiries, visit www.quest.com/contact.

Technical Support Resources

Technical support is available to Quest customers with a valid maintenance contract and customers who have trial versions. You can access the Quest Support Portal at <https://support.quest.com>

The Support Portal provides self-help tools you can use to solve problems quickly and independently, 24 hours a day, 365 days a year. The Support Portal enables you to:

- Submit and manage a Service Request
- View Knowledge Base articles

- Sign up for product notifications
- Download software and technical documentation
- View how-to-videos
- Engage in community discussions
- Chat with support engineers online
- View services to assist you with your product