

Metalogix® StoragePoint 5.9

# IBM COS Adapter Guide



© 2019 Quest Software Inc. ALL RIGHTS RESERVED.

This guide contains proprietary information protected by copyright. The software described in this guide is furnished under a software license or nondisclosure agreement. This software may be used or copied only in accordance with the terms of the applicable agreement. No part of this guide may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording for any purpose other than the purchaser's personal use without the written permission of Quest Software Inc.

The information in this document is provided in connection with Quest Software products. No license, express or implied, by estoppel or otherwise, to any intellectual property right is granted by this document or in connection with the sale of Quest Software products. EXCEPT AS SET FORTH IN THE TERMS AND CONDITIONS AS SPECIFIED IN THE LICENSE AGREEMENT FOR THIS PRODUCT, QUEST SOFTWARE ASSUMES NO LIABILITY WHATSOEVER AND DISCLAIMS ANY EXPRESS, IMPLIED OR STATUTORY WARRANTY RELATING TO ITS PRODUCTS INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTY OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, OR NON-INFRINGEMENT. IN NO EVENT SHALL QUEST SOFTWARE BE LIABLE FOR ANY DIRECT, INDIRECT, CONSEQUENTIAL, PUNITIVE, SPECIAL OR INCIDENTAL DAMAGES (INCLUDING, WITHOUT LIMITATION, DAMAGES FOR LOSS OF PROFITS, BUSINESS INTERRUPTION OR LOSS OF INFORMATION) ARISING OUT OF THE USE OR INABILITY TO USE THIS DOCUMENT, EVEN IF QUEST SOFTWARE HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES. Quest Software makes no representations or warranties with respect to the accuracy or completeness of the contents of this document and reserves the right to make changes to specifications and product descriptions at any time without notice. Quest Software does not make any commitment to update the information contained in this document.

If you have any questions regarding your potential use of this material, contact:

Quest Software Inc.  
Attn: LEGAL Dept.  
4 Polaris Way  
Aliso Viejo, CA 92656

Refer to our Web site (<https://www.quest.com>) for regional and international office information.

#### Patents

Quest Software is proud of our advanced technology. Patents and pending patents may apply to this product. For the most current information about applicable patents for this product, please visit our website at <https://www.quest.com/legal>.

#### Trademarks

Quest, the Quest logo, and Metalogix are trademarks and registered trademarks of Quest Software Inc. and its affiliates. For a complete list of Quest marks, visit <https://www.quest.com/legal/trademark-information.aspx>. All other trademarks and registered trademarks are property of their respective owners.

Metalogix® StoragePoint

Updated August 2019

Version 5.9

# Contents

<b>IBM COS</b> .....	<b>4</b>
IBM COS Adapter Connection String Parameters .....	5
Example Storage Endpoint using IBM COS Adapter .....	9
Appendix: Troubleshooting .....	10
Problem: Receiving errors on storage or retrieval of externalized content .....	10
Problem: Receiving errors on testing a storage endpoint .....	11
<b>About Us</b> .....	<b>12</b>
Contacting Quest .....	12
Technical Support Resources .....	12


# IBM COS

This section will provide you details on how to configure a storage endpoint's connection string to utilize the IBM Cloud Object Storage Adapter. Please refer to the StoragePoint Reference Guide for information on managing Storage Endpoints.

On the Application Management page, click *Storage and Backup Endpoints*.

Click *Create New Endpoint* or click the name of an existing storage endpoint that you want to edit.

Click the *Show* link next to the Advanced Adapter Settings to see the additional fields.

**Adapter**  
IBM COS  

Adapter Settings  Show Connection String

**Access Key**

**Secret Key**

**IP/Host Name**

**Use SSL**  
Yes

**Vault Name**  
  
*(Lowercase letters and "DNS Friendly" naming highly recommended.)*

**Advanced Adapter Settings** *(Hide)*

**Port**

**Strict SSL**  
No

**Provision Code**

# IBM COS Adapter Connection String Parameters

Setting	Value/Options
<p>Name</p>	<p>Enter the unique name of the Storage or Backup Endpoint.</p>
<p>Type</p> <div data-bbox="204 584 544 683"> <p>Type</p> <p><input checked="" type="radio"/> Primary <input type="radio"/> Backup</p> </div> <p>See Backup Services Settings in the Reference Guide for more information on how Backup Endpoints are used.</p>	<p><i>Primary</i>– this endpoint will be available for externalization when creating storage profiles.</p> <p><i>Backup</i>– this endpoint will be in the Backup Services dropdown on the profile page.</p> <p>The selection is locked down when saving.</p>
<p>Status</p> <div data-bbox="204 1048 611 1167"> <p>Status</p> <p>Online</p> </div>	<p><i>Online</i>– Storage Endpoint should be available to associate to a Storage Profile and accept BLOBs. (default)</p> <p><i>Offline (Read Only)</i>– A storage endpoint can be configured, but not made available for externalizing content. The BLOBs already on the endpoint are still read only.</p>
<p>Adapter</p> <div data-bbox="204 1473 616 1585"> <p>IBM COS</p> </div>	<p>Select the adapter for the endpoint that is being created.</p>
<p>Adapter Settings <input type="checkbox"/> Show Connection String</p> <p>Access Key</p> <div data-bbox="248 1727 879 1776"> <p>enter an account Access Key</p> </div>	<p>The Access Key ID provided by IBM when you signed up for the service. Required.</p>
<p>Secret Key</p> <div data-bbox="248 1906 879 1955"> <p>enter an account Secret Key</p> </div>	<p>The Secret Access Key provided by IBM when you signed up for the service. Required.</p>


Setting	Value/Options
<p>IP/Host Name</p> <input data-bbox="245 344 871 394" type="text" value="specifies explicitly the Host to use"/>	<p>IP or DNS name that represents the access point for the IBM COS service.</p>
<p>Use SSL</p> <input data-bbox="245 517 333 562" type="button" value="Yes"/>	<p>(<i>true/false</i>) Determines whether or not the adapter negotiates an SSL connection for all data (and metadata) transfers. Default = False.</p>
<p>Vault Name</p> <input data-bbox="245 775 868 819" type="text" value="enter an account Vault name"/> <i>(Lowercase letters and "DNS Friendly" naming highly recommended.)</i>	<p>The container within your IBM COS account where content associated with a storage profile will be stored. Vault names are case sensitive and unique across the entire service namespace.</p>
<p><b>Advanced Adapter Settings</b> <i>(Hide)</i></p> <p>Port</p> <input data-bbox="245 1115 871 1160" type="text" value="Enter Port number (optional)"/>	<p>Port used to access the IBM COS service. Default = 80 (443 if UseSSL is True).</p>
<p>Strict SSL</p> <input data-bbox="261 1285 349 1330" type="button" value="No"/>	<p>(<i>Yes/No</i>) If <i>UseSSL</i> is <i>Yes</i>, the <i>StrictSSL</i> flag controls whether or not the use of "self-issued" or otherwise suspicious certificates on the system will be tolerated.</p>
<p>Provision Code</p> <input data-bbox="245 1536 871 1581" type="text" value="Enter Provision Code to create Vaults (optional)"/>  <p>The provision code determines what features are enabled by way of a template. Please contact your IBM representative to get the latest provisioning codes for your organization.</p>	<p>Allows vaults to be created with specific location constraints.</p>
<p>Is WORM Device</p> <input data-bbox="301 1883 389 1928" type="button" value="No"/>	<p>If the endpoint is on a WORM (Write Once, Read Many) device, Unused BLOB Cleanup will ignore this endpoint.</p>

Setting	Value/Options
<p>Folder Content in BLOB Store</p> <p><input type="button" value="Yes"/> ▾</p> <p>Folder Scheme</p> <p><input type="text" value="YYYY/MM/DD/HH/MM"/> ▾</p>	<p><i>No</i>– Externalized content BLOBs are not placed in folders.</p> <p><i>Yes</i>– Externalized content BLOBs are placed in folders (default).</p> <p>If <i>Folder Content in BLOB Store</i> is <i>Yes</i> then you can select a date/time folder scheme from the dropdown.</p> <p>YYYY/MM/DD/HH/MM is the default.</p>
<p><input type="button" value="Test Storage Settings"/></p>	<p>The Test Storage Settings button can be used at this point, or after completing the endpoint configuration, to verify that the endpoint is accessible. For some adapters, testing the connection will create the vault if it doesn't already exist.</p>
<p>Compress Content in BLOB Store</p> <p><input type="button" value="No"/> ▾</p> <p><i>Content is compressed using the GZip/Deflate method.</i></p>	<p><i>No</i>– Externalized content BLOBs are not compressed (default).</p> <p><i>Yes</i>– Externalized content BLOBs are compressed.</p>
<p>Encryption Method for Content in BLOB Store</p> <p><input type="text" value="None"/> ▾</p>	<p><i>None</i>– Encryption will not be applied to externalized BLOBs (default).</p> <p><i>AES (128 bit)</i>– 128 bit AES encryption will be applied to externalized BLOBs.</p> <p><i>AES (256 bit)</i>– 256 bit AES encryption will be applied to externalized BLOBs.</p>

Setting	Value/Options
<p>Encryption Key Passphrase</p> <div style="border: 1px solid #ccc; padding: 5px;"> <input style="width: 150px; height: 20px;" type="text"/> <input type="button" value="Generate Key"/> </div> <p><i>Enter a passphrase to be used to generate a key or leave blank to generate a random key. The passphrase entered is <b>not</b> saved with the Endpoint.</i></p>	<p>Enter a passphrase to use when generating the encryption key. Using a passphrase will help you re-create the encryption key if necessary. You can generate a random key by leaving the box blank and clicking the <i>Generate Key</i> button. The encryption key passphrase will be hidden.</p>
<p>Generate warning notification if:</p> <p><input checked="" type="checkbox"/> <input style="width: 40px; text-align: center;" type="text" value="10"/> or more successive errors are encountered</p> <p><input type="checkbox"/> there is less than <input style="width: 40px; text-align: center;" type="text" value="10"/> <input checked="" type="radio"/> MB <input type="radio"/> % of free space</p>	<p>A warning email can be sent if the endpoint encounters errors.</p>
<p>Automatically take endpoint offline if:</p> <p><input checked="" type="checkbox"/> <input style="width: 40px; text-align: center;" type="text" value="25"/> or more successive errors are encountered</p> <p><input type="checkbox"/> there is less than <input style="width: 40px; text-align: center;" type="text" value="1"/> <input checked="" type="radio"/> MB <input type="radio"/> % of free space</p>	<p>An online storage endpoint can be automatically taken offline if it encounters errors. If a storage endpoint is taken offline automatically, BLOBs that were intended to be written to that endpoint will go to the content database.</p>
<p>Send Offline Notifications to:</p> <p><input checked="" type="checkbox"/> Use Notification Defaults</p> <p>Additional Contacts</p> <div style="border: 1px solid #ccc; padding: 2px;"> <input style="width: 150px; height: 20px;" type="text" value="admin@company.com"/> </div> <p><i>Provide a semi-colon delimited list of e-mail addresses.</i></p>	<p>Default email addresses for system error and offline notification can be entered. Check the box to include the list of Default Notification Contacts specified on the General Settings page.</p>



# Example Storage Endpoint using IBM COS Adapter

Adapter  
IBM COS  

Adapter Settings  Show Connection String

Access Key

Secret Key

IP/Host Name

Use SSL

Vault Name  
  
*(Lowercase letters and "DNS Friendly" naming highly recommended.)*

**Advanced Adapter Settings** *(Hide)*

Port

Strict SSL

Provision Code

Click the *Show Connection String* checkbox to edit the connection string. Otherwise, fill in the connection fields shown for the adapter selected. Notice that the connection string parameters are

name/value pairs separated by semi-colons.

Adapter

IBM COS

Adapter Settings  Show Connection String

Connection

```
ACCESSKEY=odMe56jNLd0oEqfkNDf;SECRETKEY=***;HOST=8.50.19.124;VAULT=storagepoint;USESSL=True;PORT=;STRICTSSL=False;PROVISIONCODE=
```

*Provide adapter-specific connection attributes. Please refer to the adapter documentation for connection string details.*

NOTE: Adapter parameters are not case-sensitive.

NOTE: You should always use a passphrase when generating encryption keys. The passphrase gives you a means of re-creating keys should they become unrecoverable or corrupt. It is very important to remember or record the passphrase outside of Metalogix StoragePoint. Otherwise, encrypted content could become irretrievable in the event of a database failure.

If you choose to externalize content you should test the storage profile settings by clicking the *Test Storage Settings* button. A message under the button will indicate whether or not the test was successful. If the test fails the message will include the error that was the root cause of the failure.

NOTE: When testing access to an endpoint from within Central Administration, the Identity of the Application Pool hosting the Central Administration Site is the one that is being used for the test. If there are different Identities used for other Web Applications in the Farm then those identities will also need access but cannot be tested from within Central Admin itself. See BLOB Store Security and Metalogix StoragePoint Required Privileges in the Metalogix StoragePoint Reference Guide.

## Appendix: Troubleshooting

### Problem: Receiving errors on storage or retrieval of externalized content

Wherever possible, StoragePoint surfaces error messages returned by the adapter either directly to the user or within the SharePoint ULS logs. You should refer to your storage platform/provider documentation for resolution to errors logged by the adapter.

## Problem: Receiving errors on testing a storage endpoint

StoragePoint may surface an error message as if the vault name has already been taken. While this is definitely possible, you should also check that the vault name is valid.

---

## About Us

### We are more than just a name

We are on a quest to make your information technology work harder for you. That is why we build community-driven software solutions that help you spend less time on IT administration and more time on business innovation. We help you modernize your data center, get you to the cloud quicker and provide the expertise, security and accessibility you need to grow your data-driven business. Combined with Quest's invitation to the global community to be a part of its innovation, and our firm commitment to ensuring customer satisfaction, we continue to deliver solutions that have a real impact on our customers today and leave a legacy we are proud of. We are challenging the status quo by transforming into a new software company. And as your partner, we work tirelessly to make sure your information technology is designed for you and by you. This is our mission, and we are in this together. Welcome to a new Quest. You are invited to Join the Innovation™.

### Our brand, our vision. Together.

Our logo reflects our story: innovation, community and support. An important part of this story begins with the letter Q. It is a perfect circle, representing our commitment to technological precision and strength. The space in the Q itself symbolizes our need to add the missing piece — you — to the community, to the new Quest.

### Contacting Quest

For sales or other inquiries, visit [www.quest.com/contact](http://www.quest.com/contact).

### Technical Support Resources

Technical support is available to Quest customers with a valid maintenance contract and customers who have trial versions. You can access the Quest Support Portal at <https://support.quest.com>

The Support Portal provides self-help tools you can use to solve problems quickly and independently, 24 hours a day, 365 days a year. The Support Portal enables you to:

- Submit and manage a Service Request
- View Knowledge Base articles

- Sign up for product notifications
- Download software and technical documentation
- View how-to-videos
- Engage in community discussions
- Chat with support engineers online
- View services to assist you with your product