

Metalogix® StoragePoint 6.1

## Caringo CASTor Adapter Guide



© 2022 Quest Software Inc. ALL RIGHTS RESERVED.

This guide contains proprietary information protected by copyright. The software described in this guide is furnished under a software license or nondisclosure agreement. This software may be used or copied only in accordance with the terms of the applicable agreement. No part of this guide may be reproduced or transmitted in any form or by any means, electronic or mechanical, including photocopying and recording for any purpose other than the purchaser's personal use without the written permission of Quest Software Inc.

The information in this document is provided in connection with Quest Software products. No license, express or implied, by estoppel or otherwise, to any intellectual property right is granted by this document or in connection with the sale of Quest Software products. EXCEPT AS SET FORTH IN THE TERMS AND CONDITIONS AS SPECIFIED IN THE LICENSE AGREEMENT FOR THIS PRODUCT, QUEST SOFTWARE ASSUMES NO LIABILITY WHATSOEVER AND DISCLAIMS ANY EXPRESS, IMPLIED OR STATUTORY WARRANTY RELATING TO ITS PRODUCTS INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTY OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, OR NON-INFRINGEMENT. IN NO EVENT SHALL QUEST SOFTWARE BE LIABLE FOR ANY DIRECT, INDIRECT, CONSEQUENTIAL, PUNITIVE, SPECIAL OR INCIDENTAL DAMAGES (INCLUDING, WITHOUT LIMITATION, DAMAGES FOR LOSS OF PROFITS, BUSINESS INTERRUPTION OR LOSS OF INFORMATION) ARISING OUT OF THE USE OR INABILITY TO USE THIS DOCUMENT, EVEN IF QUEST SOFTWARE HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES. Quest Software makes no representations or warranties with respect to the accuracy or completeness of the contents of this document and reserves the right to make changes to specifications and product descriptions at any time without notice. Quest Software does not make any commitment to update the information contained in this document.

If you have any questions regarding your potential use of this material, contact:

Quest Software Inc.  
Attn: LEGAL Dept.  
4 Polaris Way  
Aliso Viejo, CA 92656

Refer to our Web site (<https://www.quest.com>) for regional and international office information.

#### Patents


Quest Software is proud of our advanced technology. Patents and pending patents may apply to this product. For the most current information about applicable patents for this product, please visit our website at <https://www.quest.com/legal>.

#### Trademarks

Quest, the Quest logo, and Metalogix are trademarks and registered trademarks of Quest Software Inc. and its affiliates. For a complete list of Quest marks, visit <https://www.quest.com/legal/trademark-information.aspx>. All other trademarks and registered trademarks are property of their respective owners.

#### Legend

 **CAUTION:** A caution icon indicates potential damage to hardware or loss of data if instructions are not followed.

 **IMPORTANT, NOTE, TIP, MOBILE OR VIDEO:** An information icon indicates supporting information.

Metalogix® StoragePoint  
Updated July 2022  
Version 6.1

# Contents

<b>CASstor Adapter Configuration</b> .....	<b>4</b>
CASstor Adapter Connection String Parameters .....	4
Example Storage Endpoint using CASstor Adapter .....	8
Appendix: Troubleshooting .....	9
Problem: Receiving errors on storage or retrieval of externalized content. ....	9
<b>About Us</b> .....	<b>10</b>
Contacting Quest .....	10
Technical Support Resources .....	10

# CAStor Adapter Configuration

This section will provide you details on how to configure a storage endpoint's connection string to utilize the CAStor Adapter. Please refer to the StoragePoint Reference Guide for information on managing Storage Endpoints.

On the Application Management page, click *Storage and Backup Endpoints*.

Click *Create New Endpoint* or click the name of an existing storage endpoint that you want to edit.

Click the *Show* link next to the Advanced Adapter Settings to see the additional fields.

Adapter  
CAStor

**Adapter Settings**  Show Connection String

Host(s)  
enter one or more cluster hosts

**Advanced Adapter Settings (Hide)**

Port  
80

Retry  
5

Timeout  
300

## CAStor Adapter Connection String Parameters

Setting Value/Options
<p>Name</p> <p>Enter the unique name of the Storage or Backup Endpoint.</p>
<p>Type</p> <p>Type</p> <p><input checked="" type="radio"/> Primary <input type="radio"/> Backup</p> <p><i>Primary</i>– this endpoint will be available for externalization when creating storage profiles.</p>

## Setting Value/Options

*Backup*– this endpoint will be in the Backup Services dropdown on the profile page.

The selection is locked down when saving.

See Backup Services Settings in the Reference Guide for more information on how Backup Endpoints are used.


### Status



A screenshot of a web form showing a dropdown menu labeled 'Status'. The dropdown is open, and 'Online' is selected. The dropdown is set against a light gray background.

*Online*– Storage Endpoint should be available to associate to a Storage Profile and accept BLOBs. (default)

*Offline (Read Only)*– A storage endpoint can be configured, but not made available for externalizing content. The BLOBs already on the endpoint are still read only.



A screenshot of a web form showing a dropdown menu labeled 'Adapter'. The dropdown is open, and 'CASstor' is selected. There is a blue question mark icon to the right of the dropdown. The dropdown is set against a light gray background.

Select the adapter for the endpoint that is being created.



A screenshot of a web form showing a text input field labeled 'Host(s)'. The field contains the IP address '10.12.225.225'. The field is set against a light gray background.

IP or DNS name chosen at the time your storage solution was provisioned which represents the CASstor system or specific node to be used. This can also be a comma separated list of CASstor node addresses if working with a cluster.

Single host examples:

mycluster.company.com

Or

192.168.1.42

High Availability Example (in this case three hosts):

192.168.1.10, 192.168.1.20, 192.168.1.30

## Setting Value/Options

### Advanced Adapter Settings *(hide)*

Port

The port number used to communicate with the CAStor instance. Default=80.

Retry

Specifies the number of attempts to retry the network connection to CAStor before returning a failure result in case of network disruption or connectivity issues. Default = 5.

Timeout

Number of milliseconds to wait for a response to any request before considering it an excessively long wait and raising an error condition. Default = 300.

Folder Content in BLOB Store

 ▾

Folder Scheme

 ▾

*No*– Externalized content BLOBs are not placed in folders (default).

*Yes*– Externalized content BLOBs are placed in folders.

If *Folder Content in BLOB Store* is *Yes* then you can select a date/time folder scheme from the dropdown.

YYYY/MM/DD/HH/MM is the default.

The Test Storage Settings button can be used at this point, or after completing the endpoint configuration, to verify that the endpoint is accessible.

Compress Content in BLOB Store

 ▾

*Content is compressed using the GZip/Deflate method.*

*No*– Externalized content BLOBs are not compressed (default).

*Yes*– Externalized content BLOBs are compressed.

## Setting Value/Options

Encryption Method for Content in BLOB Store

None

*None*– Encryption will not be applied to externalized BLOBs (default).

*AES (128 bit)*– 128 bit AES encryption will be applied to externalized BLOBs.

*AES (256 bit)*– 256 bit AES encryption will be applied to externalized BLOBs.

Encryption Key Passphrase

Generate Key

*Enter a passphrase to be used to generate a key or leave blank to generate a random key. The pass phrase entered is **not** saved with the Endpoint.*

Enter a passphrase to use when generating the encryption key. Using a passphrase will help you re-create the encryption key if necessary. You can generate a random key by leaving the box blank and clicking the *Generate Key* button. The encryption key passphrase will be hidden.

Generate warning notification if:

- 10 or more successive errors are encountered
- there is less than 10  MB  % of free space

A warning email can be sent if it encounters errors.

Automatically take endpoint offline if:

- 25 or more successive errors are encountered
- there is less than 1  MB  % of free space

An online storage endpoint can be automatically taken offline if it encounters errors. If a storage endpoint is taken offline automatically, BLOBs that were intended to be written to that endpoint will go to the content database.

Send Offline Notifications to:

Use Notification Defaults

Additional Contacts

admin@company.com

*Provide a semi-colon delimited list of e-mail addresses.*

Default email addresses for system error and offline notification can be entered. Check the box to include the list of Default Notification Contacts specified on the General Settings page.

# Example Storage Endpoint using CASTor Adapter

The screenshot shows the 'Adapter Settings' window for the 'CASTor' adapter. The 'Adapter' dropdown is set to 'CASTor'. The 'Host(s)' field contains '10.12.225.225'. Under 'Advanced Adapter Settings (Hide)', the 'Port' is '80', 'Retry' is '3', and 'Timeout' is '300'. The 'Show Connection String' checkbox is unchecked.

Click the *Show Connection String* checkbox to edit the connection string. Otherwise, fill in the connection fields shown for the adapter selected. Notice that the connection string parameters are name/value pairs separated by semi-colons.

The screenshot shows the 'Adapter Settings' window for the 'CASTor' adapter. The 'Adapter' dropdown is set to 'CASTor'. The 'Show Connection String' checkbox is checked. The 'Connection' text area contains the string: 'HOST=10.12.225.225;PORT=80;RETRY=5;TIMEOUT=300;'. Below the text area is a note: 'Provide adapter-specific connection attributes. Please refer to the adapter documentation for connection string details.'

**i** | **NOTE:** Adapter parameters are not case-sensitive.

**i** | **NOTE:** You should always use a passphrase when generating encryption keys. The passphrase gives you a means of re-creating keys should they become unrecoverable or corrupt. It is very important to remember or record the passphrase outside of Metalogix StoragePoint. Otherwise, encrypted content could become irretrievable in the event of a database failure.

If you choose to externalize content you should test the storage profile settings by clicking the *Test Storage Settings* button. A message under the button will indicate whether or not the test was successful. If the test fails the message will include the error that was the root cause of the failure.



**i** | **NOTE:** When testing access to an endpoint from within Central Administration, the Identity of the Application Pool hosting the Central Administration Site is the one that is being used for the test. If there are different Identities used for other Web Applications in the Farm then those identities will also need access but cannot be tested from within Central Admin itself. See BLOB Store Security and Metalogix StoragePoint Required Privileges in the Metalogix StoragePoint Reference Guide.

## Appendix: Troubleshooting

### Problem: Receiving errors on storage or retrieval of externalized content.

Wherever possible, StoragePoint surfaces error messages returned by CASTor either directly to the user or within the SharePoint ULS logs. You should refer to your CASTor documentation for errors logged by the CASTor Adapter.

---

## About Us

Quest creates software solutions that make the benefits of new technology real in an increasingly complex IT landscape. From database and systems management, to Active Directory and Office 365 management, and cyber security resilience, Quest helps customers solve their next IT challenge now. Around the globe, more than 130,000 companies and 95% of the Fortune 500 count on Quest to deliver proactive management and monitoring for the next enterprise initiative, find the next solution for complex Microsoft challenges and stay ahead of the next threat. Quest Software. Where next meets now. For more information, visit [www.quest.com](http://www.quest.com).

## Contacting Quest

For sales or other inquiries, visit [www.quest.com/contact](http://www.quest.com/contact).

## Technical Support Resources

Technical support is available to Quest customers with a valid maintenance contract and customers who have trial versions. You can access the Quest Support Portal at <https://support.quest.com>

The Support Portal provides self-help tools you can use to solve problems quickly and independently, 24 hours a day, 365 days a year. The Support Portal enables you to:

- Submit and manage a Service Request
- View Knowledge Base articles
- Sign up for product notifications
- Download software and technical documentation
- View how-to-videos
- Engage in community discussions
- Chat with support engineers online
- View services to assist you with your product